

Configuring Terminal Lines and Modem Support

This chapter explains how to configure lines and terminal settings. The LightStream 1010 ATM switch has two types of terminal lines: one console line and one auxiliary line. Most line setup is the same for all types of lines, but certain commands, such as those having to do with modem control and Serial Line Internet Protocol (SLIP)/Point-to-Point Protocol (PPP) support, apply to the auxiliary port only.

Note For a complete description of the commands mentioned in this chapter, refer to the *LightStream 1010 ATM Switch Command Reference* publication.

Line Configuration Task List

The following sections describe line configuration tasks. One of the first things you will need to do for line configuration is to set up the lines for the terminals or other asynchronous devices attached to them. The parameters for each line are configured next. However, the tasks you perform and the order in which you perform them are determined entirely by the requirements of your network environment.

Perform one or more of the tasks in the following sections to configure your LightStream 1010 line connections:

- Prepare to Configure Lines
- Set Communication Parameters
- Configure Automatic Baud Detection
- Change the Default Privilege Level for Lines
- Configure Flow Control for Communications
- Define a Command String for Automatic Execution
- Create Packet Dispatch Sequences
- Specify the Transport Protocol for a Specific Line
- Establish Terminal Session Limits
- Set Up Modem Control on the Auxiliary Port
- Support for the Line Printer Daemon Protocol
- Support Reverse TCP Connections
- Define Terminal Operation Characteristics

- Configure Automatic Protocol Startup
- Configure Terminal Banner Messages
- Configure Telnet Capabilities

Prepare to Configure Lines

Line configuration mode is used to set the terminal-specific parameters. From line configuration mode, you can enter special commands called line configuration commands that affect the auxiliary or console port line you have specified. To enter line configuration mode, complete the following task:

Task	Command
Step 1 At the privileged EXEC prompt, enter configuration mode from the terminal.	configure ¹ [terminal]
Step 2 From global configuration mode, begin to configure an auxiliary, console, or virtual terminal line.	line [aux console vty] line-number [ending-line-number]

1. This command is documented in the *LightStream 1010 ATM Switch Command Reference* publication.

For example, to configure line parameters for the auxiliary port at Step 2 in the preceding task, you would enter the following:

```
Switch(config)# line aux 0
```

The auxiliary relative line number must be 0. See the **modem** line configuration commands in the section “Set Up Modem Control on the Auxiliary Port” later in this chapter to set up modem support on the auxiliary port.

The terminal from which you locally configure the LightStream 1010 ATM switch is attached to the console port. To configure line parameters for the console port at Step 2 in the preceding task, you would enter the following:

```
Switch(config)# line con 0
```

The console relative line number must be 0.

Configuring the console port or virtual terminal lines allows you to perform such tasks as setting communication parameters, specifying autobaud connections, and configuring terminal operating parameters for the terminal you are using. These tasks are described later in this chapter.

Example of Creating Additional Virtual Terminal Lines

In the following example, the user creates and configures the maximum 4 virtual terminal lines with the “no login” feature:

```
Switch(config)#line vty 0 4
Switch(config-line)#no login
```

Example of Eliminating Virtual Terminal Lines

In the following example, the user eliminates virtual terminal line number 4 and all higher-numbered virtual terminal lines. Only virtual terminal lines 0 to 3 will remain.

```
Switch(config)#no line vty 4
```

Set Communication Parameters

The LightStream 1010 ATM switch supplies default serial communication parameters for terminal and other serial device operation. You can change these parameters as necessary to meet the requirements of the terminal or host to which you are attached. To do so, perform one or more of the following tasks in line configuration mode:

Task	Command
Set the line speed. Choose from line speed, transmit speed, or receive speed. Speed applies to the auxiliary port only.	speed <i>bps</i> txspeed <i>bps</i> rxspeed <i>bps</i>
Set the data bits.	databits { 5 6 7 8 }
Set the stop bits.	stopbits { 1 1.5 2 }
Set the parity bit.	parity { none even odd space mark }

Example

The following example configures the auxiliary line with a speed of 19200 bit per second:

```
Switch(config)#line aux 0
Switch(config-line)#speed 19200
```

Configure Automatic Baud Detection

You can configure a terminal to automatically detect the baud rate being used over an asynchronous serial line. This command applies to the auxiliary port only. To set up automatic baud detection, perform the following task in line configuration mode:

Task	Command
Set the terminal to automatically detect the baud rate.	autobaud

To start communications using automatic baud detection, press Returns multiple times at the terminal. A 600-, 1800-, or 19200-baud line requires three Returns to detect the baud rate. A line at any other baud rate requires only two Returns. If you press Return after the baud rate is detected, the EXEC simply displays another system prompt.

Change the Default Privilege Level for Lines

To change the default privilege level for a given line or a group of lines, perform the following task in line configuration mode:

Task	Command
Specify a default privilege level for a line.	privilege level <i>level</i> ¹

1. This command is documented in the *LightStream 1010 ATM Switch Command Reference* publication.

Configure Flow Control for Communications

On the auxiliary port, you can set both hardware and software flow control between the LightStream 1010 ATM switch and devices attached to it. Both types of flow control are bidirectional. When you specify **software** flow control, an additional keyword specifies the direction: **in** causes the

LightStream 1010 ATM switch to listen to flow control from the attached device, and **out** causes the LightStream 1010 ATM switch to send flow control information to the attached device. If you do not specify a direction, the LightStream 1010 ATM switch enables software flow control in both directions.

For software flow control, the default stop and start characters are Ctrl-S and Ctrl-Q (XOFF and XON), respectively. However, you can define characters or character sequences that signal the start and end of data transmission when software flow control is in effect. This capability is useful for providing control of data over the serial line.

You can also specify hardware flow control. For information about setting up the RS-232 line, see the hardware installation and maintenance manual for your product.

To configure flow control between the LightStream 1010 ATM switch and attached device, perform one or more of the following tasks in line configuration mode:

Task	Command
Set the terminal flow control.	flowcontrol { none software [in out] hardware [in out] }
Set the flow control start character.	start-character <i>ascii-number</i>
Set the flow control stop character.	stop-character <i>ascii-number</i>

Define a Command String for Automatic Execution

You can set up a command that will automatically execute upon connection to another host. Any appropriate EXEC command and any switch or host name that occurs with the EXEC command is allowed. To do so, perform the following task in line configuration mode:

Task	Command
Define a command to be automatically executed.	autocommand <i>command</i>

Create Packet Dispatch Sequences

The LightStream 1010 ATM switch supports configuration of dispatch sequences. You can set up dispatch characters that allow packets to be buffered, then transmitted upon receipt of a character. These characters are useful on an auxiliary port only, and then only if you have some special-purpose device hooked up.

To configure a dispatch sequence, perform one or both of the following tasks as needed for your particular system in line configuration mode:

Task	Command
Define one or more characters that trigger packet transmission for a particular line.	dispatch-character <i>ascii-number1</i> [<i>ascii-number2</i> . . . <i>ascii-number</i>]
Set the dispatch timer.	dispatch-timeout <i>milliseconds</i>

Specify the Transport Protocol for a Specific Line

You can selectively specify the protocols allowed on individual lines. You can set the protocol for incoming and outgoing connections and change the default (preferred) protocol for a line. The default transport protocol is Telnet.

Selecting which command to use is determined by whether it is for incoming or outgoing connections or is being used as a default (preferred) selection.

Perform one or more of the following tasks in line configuration mode to specify transport protocols:

Task	Command
Define which protocols can be used to connect to a specific line of the LightStream 1010 ATM switch.	transport input { mop telnet none }
Determine the protocols that can be used for outgoing connections from a line.	transport output { telnet none }
Specify the protocol for the LightStream 1010 ATM switch to use if the user did not specify a protocol.	transport preferred telnet
Prevent errant connection attempts.	transport preferred none

The system accepts a host name entry at the EXEC system prompt as a Telnet command. If you mistype the host name, the system interprets the entry as an incorrect Telnet command and provides an error message indicating that the host does not exist. The **transport preferred none** command disables this option so that if you mistype a command at the EXEC prompt, the system will not attempt to make a Telnet connection.

Establish Terminal Session Limits

You might need to control terminal sessions in high-traffic areas to provide resources for all users. You can define these limitations for terminal sessions:

- Maximum number of sessions
- Idle session timeout interval or absolute timeout interval

To control terminal sessions, perform one or more of the following tasks in line configuration mode:

Task	Command
Set the maximum number of sessions.	session-limit <i>session-number</i>
Set the idle session timeout interval.	session-timeout <i>minutes</i> [output]
or	or
Set the absolute timeout interval.	absolute-timeout <i>minutes</i>
Warn users of impending timeouts set with the absolute-timeout command.	logout-warning [<i>seconds</i>]

Note The **absolute-timeout** command overrides any timeouts set through AppleTalk Remote Access (ARA) protocol.

Set Up Modem Control on the Auxiliary Port

You can configure modem control on the auxiliary port of the LightStream 1010 ATM switch. The auxiliary port is a standard RS-232-C DB-25 connector. Its output and input signals are listed in Table 3-1.

Table 3-1 Auxiliary Port Signals

Pin	Signal	Direction	Description
2	TxD	--->	Transmit data
3	RxD	<---	Receive data
4	RTS	--->	Request to send (used for hardware flow control)
5	CTS	<---	Clear to send (used for hardware flow control)
6	DSR	<---	Data set ready
7	Signal ground	--	Signal ground
8	CD	<---	Carrier detect (used for modem control)
20	DTR	--->	Data terminal ready (used for modem control only)

Configure modem control on the LightStream 1010 ATM switch performing the following tasks:

- Configure Automatic Dialing
- Close Modem Connections
- Configure a Line to Automatically Answer a Modem
- Support a Dial-In Modem
- Support Reverse Modem Connections and Prevent Incoming Calls
- Support Dial-In and Dial-Out Modems
- Configure a Line Timeout Interval
- Configure Rotary Groups
- Configure Automatic Line Disconnect
- Configure High-Speed Modem Support
- Configure Chat Scripts for Asynchronous Lines


State diagrams accompany some of the tasks in the following sections to illustrate how the modem control works. The diagrams show two processes:

- The *create daemon* process creates a TTY daemon that handles the incoming network connection.
- The *create EXEC* process creates the process that interprets user commands. (Refer to Figure 3-1 through Figure 3-6.)

In the diagrams, the current signal state and the signal line is watching are listed inside each box. The state of the line (as displayed by the EXEC command **show line**) is listed next to the box. Events that change that state appear in italics along the event path, with the software actions described within the ovals.

Figure 3-1 illustrates line behavior when no modem control is set. The DTR output is always high, and CTS and RING are completely ignored. The LightStream 1010 ATM switch creates an EXEC when the user types the activation character. Incoming TCP connections occur instantly if the line is not in use and can be closed only by the remote host.

Figure 3-1 EXEC and Daemon Creation on a Line with No Modem Control



Configure Automatic Dialing

With the dial-up capability, you can set a modem to automatically dial the phone number of a remote LightStream 1010 ATM switch. This feature offers cost savings because phone line connections are made as needed. You only pay for using the phone line when there is data to be received or sent. To configure a line for automatic dialing, perform the following task in line configuration mode:

Task	Command
Configure a line to initiate automatic dialing.	modem dtr-active

Close Modem Connections


You can configure a line to close connections from a user's terminal when the terminal is turned off, and prevent inbound connections to devices that are out of service. To do so, perform the following task in line configuration mode:

Task	Command
Configure a line to close connections.	modem cts-required

Figure 3-2 illustrates the **modem cts-required** process. This form of modem control requires that CTS be high throughout the use of the line. If CTS is not high, the user's typed input is ignored and incoming connections are refused (or step to the next line in a rotary group).

Note In order for a LightStream 1010 ATM switch to reliably detect a CTS signal change, the signal must remain in the new state for at least one full second.

Figure 3-2 EXEC and Daemon Creation on a Line Configured for Continuous CTS



Configure a Line to Automatically Answer a Modem

You can configure a line to automatically answer a modem. You would also configure the modem to answer the telephone on its own as long as DTR is high, drop connections when DTR is low, and use its Carrier Detect (CD) signal to accurately reflect the presence of carrier (configuring the


modem is a modem-dependent process). Wire the modem's CD signal (generally pin-8) to the LightStream 1010 ATM switch's RING input (pin-22) and perform the following task in line configuration mode:

Task	Command
Configure a line to automatically answer a modem.	modem ri-is-cd

You can turn on the modem's hardware flow control independently to act on the status of the LightStream 1010 ATM switch's CTS input. Wire CTS to whatever signal the modem uses for hardware flow control. If the modem expects to control hardware flow in both directions, you might also need to wire the modem's flow control input to some other signal that the LightStream 1010 ATM switch always has high (such as DTR).

Figure 3-3 illustrates the **modem ri-is-cd** process. When the LightStream 1010 ATM switch detects a signal on the RING input of an idle line, it starts an EXEC or autobaud process on that line. If the RING signal disappears on an active line, the LightStream 1010 ATM switch closes any open network connections and terminates the EXEC. If the user exits the EXEC or the LightStream 1010 ATM switch terminates it because of no user input, the line hangs up the modem by lowering the DTR signal for five seconds. After five seconds, the modem is ready to accept another call.

Figure 3-3 EXEC Creation on a Line Configured for a High-Speed Dial-up Modem




Support a Dial-In Modem

The LightStream 1010 ATM switch supports dial-in modems that use DTR to control the off-hook status of the telephone line. Perform the following task in line configuration mode to configure the line to support this feature:

Task	Command
Configure a line for a dial-in modem.	modem callin

Figure 3-4 illustrates the **modem callin** process. When a modem dialing line is idle, it has DTR in a low state and waits for a transition to occur on the RING input. This transition causes the line to raise DTR and start watching the CTS signal from the modem. After the modem raises CTS, the LightStream 1010 ATM switch creates an EXEC on the line. If the timeout interval (set with the **modem answer-timeout** command) passes before the modem raises CTS, the line lowers DTR and returns to the idle state.

Figure 3-4 EXEC Creation on a Line Configured for Modem Callin



Note The **modem callin** and **modem cts-required** line configuration commands are useful for SLIP operation. These commands ensure that when the line is hung up or CTS drops, the line reverts from SLIP mode to normal interactive mode. These commands do not work if you use the **async dedicated** command to put the line in network mode permanently.

Although you can use the **modem callin** line configuration command with newer modems, the **modem ri-is-cd** line configuration command described earlier in this section is more appropriate. The **modem ri-is-cd** command frees up CTS for hardware flow control. Modern modems do not require the assertion of DTR to take a phone line off-hook.


Support Reverse Modem Connections and Prevent Incoming Calls

The LightStream 1010 ATM switch supports ports connected to computers that are connected to modems. You can configure the LightStream 1010 ATM switch to behave somewhat like a modem by performing the following task in line configuration mode. This command also prevents incoming calls.

Task	Command
Configure a line for reverse connections and prevent incoming calls.	modem callout

Figure 3-5 illustrates the **modem callout** process. When the LightStream 1010 ATM switch receives an incoming connection, it raises DTR and waits to see if the CTS becomes high as an indication that the host has noticed its signal. If the host does not respond within the interval set with the **modem answer-timeout** subcommand, the LightStream 1010 ATM switch lowers DTR and drops the connection.

Figure 3-5 Daemon Creation on a Line Configured for Modem Callout




Support Dial-In and Dial-Out Modems

You can configure a line for both incoming and outgoing calls by performing the following task in line configuration mode:

Task	Command
Configure a line for both incoming and outgoing calls.	modem in-out

Figure 3-6 illustrates the **modem in-out** process. If the line is activated by raising RING, it behaves exactly as a line configured with the **modem ri-is-cd** subcommand described earlier. If the line is activated by an incoming TCP connection, the line behaves similarly to a nonmodem line.

Figure 3-6 EXEC and Daemon Creation on a Line Configured for Incoming and Outgoing Calls



Note If your system incorporates dial-out modems, consider using access lists to prevent unauthorized use.

Configure a Line Timeout Interval

You can change the interval that the LightStream 1010 ATM switch waits for CTS after raising DTR in response to RING from the default of 15 seconds. To do so, perform the following task in line configuration mode. The timeout applies to the **modem callin** command only.

Task	Command
Configure modem line timing.	modem answer-timeout <i>seconds</i>

Configure Rotary Groups

Connections can be made to the next free line in a group of lines, also called a rotary or hunt group. A line can be in only one rotary group; a rotary group can consist of a single line or several contiguous lines. The console line (line 0) cannot be in a rotary group.

You might want to assign the rotary with the single auxiliary port line, because the auxiliary port is not necessarily the same line number on all hardware. By putting it in a rotary group, you do not have to track the actual line number. Another reason to use a rotary group is that if the device supports local area transport (LAT), an inbound service can only be bound to a rotary group; it cannot be bound to a port number.

To configure a rotary group, perform the following task in line configuration mode:

Task	Command
Add a line to the specified rotary group.	rotary <i>group</i>

Configure Automatic Line Disconnect

You can configure automatic line disconnect by performing the following task in line configuration mode:

Task	Command
Configure automatic line disconnect.	autohangup

The command causes the EXEC to issue the **exit** command when the last connection closes. This feature is useful for UNIX-to-UNIX Copy Program (UUCP) applications that require this behavior, because UUCP scripts cannot issue the command that hangs up the telephone.

Configure High-Speed Modem Support

Dial-up modems that operate over normal dial-up telephone lines at speeds of 9600 bits per second (bps) and higher are now available. These modems do not operate at a guaranteed throughput; instead, they operate at a speed dependent on the quality of the line, the effectiveness of data compression algorithms on the data being transmitted, and other variables. These modems use hardware flow control to stop the data from reaching the host by toggling an RS-232 signal when they cannot accept any more.

In addition to hardware flow control, dial-up modems require special software handling. For example, they must be configured to create an EXEC when a user dials in and to hang up when the user exits the EXEC. These modems must also be configured to close any existing network connections if the telephone line hangs up in the middle of a session.

Your LightStream 1010 ATM switch supports hardware flow control on its CTS input, which is also used by the normal modem handshake.

Perform the following tasks to configure and use a high-speed modem:

Task	Command
Step 1 In line configuration mode, enable outgoing hardware flow control based on the CTS input.	flowcontrol hardware
Step 2 In EXEC mode, display informational messages about modem control events, such as signal transitions and autobaud progress, on the console terminal.	debug modem
Step 3 In EXEC mode, display the status of a line. In the detailed command output, a Status line with “Idle” identifies inactive modem ri-is-cd lines and all other modem lines; a Status line with “Ready” identifies lines in use.	show line ¹
Step 4 In EXEC mode, close all the connections on a line and hang up the modem.	clear line

1. This command is documented in the *LightStream 1010 ATM Switch Command Reference* publication.

Configure Chat Scripts for Asynchronous Lines

Chat scripts are strings of text used to send commands for modem dialing, logging onto remote systems, and initializing asynchronous devices connected to the line. On a LightStream 1010 ATM switch, chat scripts can be configured on the auxiliary port only. A chat script must be defined for dialing out on asynchronous lines.

You can configure chat scripts manually, or you can configure a line to activate a chat script in response to one of the following events on a line:

- Line activation
- Incoming connection initiation
- Line resets
- LightStream 1010 ATM switch startup

To use a chat script, perform the following steps:

- Step 1** Create a chat script.
- Step 2** Configure the line so that a chat script is activated when a specific event occurs, or start a chat script manually.

Create a Chat Script

To define a chat script, perform the following task in global configuration mode:

Task	Command
Create a script that will place a call on a modem, log on to a remote system, or initialize an asynchronous device on a line.	chat-script <i>script-name expect-send</i> ¹

1. This command is documented in the *LightStream 1010 ATM Switch Command Reference* publication.

A limited list of keywords is supported along with expect/send pairs. Send strings can have special escape modifiers.

We recommend that you write two chat scripts: one modem chat script for placing a call and another system or login chat script to log on to remote systems, where required.

When you create a script name, include the modem vendor, type, and modulation separated by hyphens (-). For example, if you have a Telebit t3000 modem that uses V.32bis modulation, your script name would be *telebit-t3000-v32bis*.

Configure the Line to Activate Chat Scripts

Chat scripts can be activated by any of five events, each corresponding to a different version of the **script** line configuration command. To start a chat script manually at any point, refer to the section “Start a Chat Script Manually.”

To define a chat script to start automatically when a specific event occurs, perform the following tasks in line configuration mode:

Task	Command
Start a chat script on a line when the line is activated (every time a command EXEC is started on the line).	script activation <i>regex</i> ¹
Start a chat script on a line when a network connection is made to the line.	script connection <i>regex</i>
Specify a modem script for DDR on a line.	script dialer <i>regex</i>
Start a chat script on a line whenever the line is reset.	script reset <i>regex</i>
Start a chat script on a line whenever the system is started up.	script startup <i>regex</i>

1. The argument *regex* is a regular expression matched to a script name that has already been defined with the **chat-script** command.

Start a Chat Script Manually

You can start a chat script manually on any line that is currently not active by performing the following task in privileged EXEC mode:

Task	Command
Start a chat script manually on any asynchronous line.	start-chat <i>regex</i> [aux 0 [<i>dialer-string</i>]]

If you do not specify the line number, the script runs on the current line. If the line specified is already in use, you cannot start the chat script. A message appears indicating that the line is already in use.

Support for the Line Printer Daemon Protocol

We support a subset of the Berkeley UNIX line printer daemon (LPD) protocol used to send print jobs between UNIX systems. This subset of the LPD protocol permits:

- Improved status information
- Cancellation of print jobs
- Confirmation of successful printing and automatic retry for common failure cases
- Use of standard UNIX software

The Cisco implementation of LPD permits you to configure a printer to allow several types of data to be sent as print jobs (for example, PostScript or raw text).

Configuring a Printer

To configure a printer for the LPD protocol, perform the following task in global configuration mode:

Task	Command
Configure printer and specify a tty line (or lines) for the device.	printer <i>printername</i> { <i>line number</i> rotary number } [newline-convert]

If you use the **printer** command, you will also have to modify the `/etc/printcap` file on the UNIX system to include the definition of the remote printer on the access server. Use the optional **newline-convert** keyword on UNIX systems that do not handle single character line terminators to convert a new line to a carriage-return, linefeed sequence.

The following example includes the configuration of the printer Saturn on the host Memphis:

```
comm1pt|Printer on cisco AccessServer:\
:rm+memphis:rp+saturon:\
:sd+/usr/spool/lpd/comm1pt:\
:lf=?var/log/lpd/comm1pt:
```

The content of the actual file may differ depending on the configuration of your system.

Support Reverse TCP Connections

In addition to initiating connections, the LightStream 1010 ATM switch can receive incoming connections on the auxiliary port. This capability allows you to attach serial printers, modems, and other shared peripherals to the LightStream 1010 ATM switch and drive them remotely from other systems. The LightStream 1010 ATM switch supports reverse TCP connections.

The specific TCP port or socket to which you attach the peripheral device determines the type of service the LightStream 1010 ATM switch provides on that line. When you attach the serial lines of a computer system or a data terminal switch to the auxiliary port of the LightStream 1010 ATM switch, the LightStream 1010 ATM switch acts as a network front end for a host that does not support the TCP/IP protocols. This arrangement is sometimes called *front-ending* or *reverse connection mode*.

To connect the auxiliary port, the remote host or terminal must specify a particular TCP port on the LightStream 1010 ATM switch. If Telnet protocols are required, that port is 2000 (decimal) plus the decimal value of the line number.

If a raw TCP stream is required, the port is 4000 (decimal) plus the decimal line number. The raw TCP stream is usually the required mode for sending data to a printer.

The Telnet protocol requires that carriage return characters be translated into carriage return and linefeed character pairs. You can turn this translation off by specifying the Telnet binary mode option. To specify this option, connect to port 6000 (decimal) plus the decimal line number.

Define Terminal Operation Characteristics

In line configuration mode, you can set terminal operation characteristics that will be in operation for that line until the next time you change the line parameters.

Alternatively, you can temporarily change the line settings with the **terminal** EXEC commands provided in the chapter “Understanding the User Interfaces for the LightStream 1010 ATM Switch.”

Define the terminal operation characteristics by performing the following tasks:

- Specify the Terminal Type
- Set the Terminal Screen Length and Width
- Define Escape Character and Other Key Sequences
- Specify the International Character Display
- Set Character Padding
- Disable Enhanced Editing Mode
- Set a Terminal-Locking Mechanism
- Dedicate a Line to a Particular User
- Provide Line Connection Information after the Login Prompt
- Enable Password Checking at Login
- Create Packet Dispatch Sequences

Specify the Terminal Type

You can specify the type of terminal connected to a line. This feature has two benefits: it provides a record of the type of terminal attached to a line, and it can be used in Telnet terminal negotiations to inform the remote host of the terminal type for display management. To specify the terminal type, perform the following task in line configuration mode:

Task	Command
Specify the terminal type.	terminal-type <i>terminal-name</i>

Set the Terminal Screen Length and Width

By default, the LightStream 1010 ATM switch provides a screen display of 24 lines by 80 characters. You can reconfigure these values if they do not meet the needs of your terminal by performing the following tasks in line configuration mode:

Task	Command
Set the screen length.	length <i>screen-length</i>
Set the screen width.	width <i>characters</i>

The values set can be learned by some host systems that use this type of information in terminal negotiation. Set a value of zero for the screen length to disable pausing between screens of output.

Define Escape Character and Other Key Sequences

You can define or modify the default key sequences to execute functions for system escape, terminal activation, disconnect, and terminal pause. To define or change the default sequence, perform one or more of the following tasks in line configuration mode:

Task	Command
Change the system escape sequence. The escape sequence indicates that the codes that follow have special meaning. The default sequence is Ctrl-^.	escape-character <i>ascii-number</i>

Task	Command
Define a session activation sequence or character. Typing this sequence at a vacant terminal begins a terminal session. The default key is Return.	activation-character <i>ascii-number</i>
Define the session disconnect sequence or character. Typing this sequence at a terminal ends the session with the LightStream 1010 ATM switch. There is no default sequence.	disconnect-character <i>ascii-number</i>
Define the hold sequence or character that causes output to the terminal screen to pause. There is no default sequence. To continue the output, type any character after the hold character. To use the hold character in normal communications, precede it with the escape character.	hold-character <i>ascii-number</i>

You can reinstate the default value for the escape character or activation character by using the **no** form of the command. For example, issuing the **no escape-character** line configuration command returns the escape character to Ctrl-^.

Note If you are using the **autoselect** command, do not change the activation character from the default value of Return. If you change this default, **autoselect** may not function immediately.

Specify the International Character Display

You can use a 7-bit character set (such as ASCII) or you can enable a full 8-bit international character set (such as ISO 8859) to allow special graphical and international characters for use in banners and prompts, and to add special characters such as software flow control. These settings can be configured globally by interface or locally at the user level. Use the following criteria for determining the configuration mode to use to set up this feature:

- If a large number of connected terminals support nondefault ASCII bit settings, use the global configuration commands.
- If only a few of the connected terminals support nondefault ASCII bit settings, use line configuration commands or the EXEC local terminal setting commands.

Note Setting the EXEC character width to 8 bits can cause failures. If a user on a terminal that is sending parity enters the command **help**, an `unrecognized command` message appears because the system is reading all eight bits, although the eighth bit is not needed for the **help** command.

To specify a character set on a global basis, perform *one or both* of the following tasks in global configuration mode:

Task	Command
Specify the character set used in EXEC and configuration command characters.	default-value exec-character-bits {7 8}
Specify the character set used in special characters such as software flow control, hold, escape, and disconnect characters.	default-value special-character-bits {7 8}

To specify a character set based on hardware or software, or on a per-line basis, perform the appropriate task in line configuration mode, as follows:

Task	Command
Set the number of databits per character that are generated and interpreted by hardware.	databits {5 6 7 8}
Set the number of databits per character that are generated and interpreted by software.	data-character-bits {7 8}
Specify the character set used in EXEC and configuration command characters on a per-line basis.	exec-character-bits {7 8}
Specify the character set used in special characters such as software flow control, hold, escape, and disconnect characters on a per-line basis.	special-character-bits {7 8}

Note If you are using the **autoselect** function, let the activation character default to Return, and **exec-character-bits** default to 7. If you change these defaults, the application will not recognize the activation request.

Set Character Padding

You can change the character padding on a specific output character. Character padding adds a number of null bytes to the end of the string and can be used to make a string an expected length for conformity. To set character padding, perform the following task in line configuration mode:

Task	Command
Set padding on a specific output character for the specified line.	padding <i>ascii-number count</i>

Disable Enhanced Editing Mode

To disable enhanced editing mode and revert to the editing mode of previous software releases, perform the following task in line configuration mode:

Task	Command
Disable the enhanced editing features for a particular line.	no editing ¹

1. This command is documented in the *LightStream 1010 ATM Switch Command Reference* publication.

You might disable enhanced editing if you have prebuilt scripts, for example, that do not interact well when enhanced editing is enabled. You can reenable enhanced editing mode with the **editing** command.

Set a Terminal-Locking Mechanism

You can enable a terminal-locking mechanism that allows a terminal to be temporarily locked by performing the following task in global configuration mode:

Task	Command
Enable a temporary terminal locking mechanism.	lockable

After you configure the line as lockable, you must still issue the **lock** EXEC command to lock the keyboard.

Dedicate a Line to a Particular User

By default, user-set terminal parameters are cleared with the EXEC command **exit** or when the interval set with the **exec-timeout** line configuration command has passed. However, you can configure a line so that user-set terminal parameters are saved between sessions by performing the following task in line configuration mode:

Task	Command
Configure a line so that the terminal parameters the user sets remain in effect between terminal sessions.	private

Provide Line Connection Information after the Login Prompt

You can provide the host name, line number, and location each time an EXEC is started or an incoming connection is made. The line number banner appears immediately after the EXEC banner or incoming banner. It is useful for tracking problems with modems because it lists the host and line for the modem connection. Modem information is also included if applicable.

To provide service line number information, perform the following task in global configuration mode:

Task	Command
Provide service line number information after the EXEC or incoming banner.	service linenum

Enable Password Checking at Login

You can enable password checking on a particular line so that the user is prompted to enter a password at the system login screen. You must then also specify a password. Perform the following tasks in line configuration mode:

Task	Command
Step 1 Enable password checking on a per-line basis using the password specified with the password command.	login
Step 2 Assign a password to a particular line.	password <i>password</i>

You can enable password checking on a per-user basis, in which case authentication is based on the username specified with the **username** global configuration command, as described in the “Configuring System Management Functions” chapter. To enable this type of password checking, perform one of the following tasks in line configuration mode:

Task	Command
Enable password checking on a per-user basis using the username and password specified with the username global configuration command.	login local
Select the TACACS-style user ID and password-checking mechanism.	login tacacs or login authentication { default <i>list-name</i> }

Use the **login tacacs** command with TACACS and extended TACACS. Use the **login authentication** command with AAA/TACACS+.

By default, virtual terminals require passwords. If you do not set a password for a virtual terminal, it responds to attempted connections by displaying an error message and closing the connection. Use the **no login** command to disable this behavior and allow connections without a password.

For other access control tasks and password restrictions, including the **enable password** global configuration command that restricts access to privileged mode, see the “Configuring System Management Functions” chapter.

Checking Password Examples

The following example shows password checking enabled for a virtual terminal line 1:

```
Switch(config)#line vty 1
Switch(config-line)#login
Switch(config-line)#password letmein
```

The following example shows password checking enabled on a user basis:

```
Switch(config)#username jksmith password 0 letmein
Switch(config)#username lmjones password 0 littlerock
Switch(config)#line vty 1
Switch(config-line)#login local
```

Create Packet Dispatch Sequences

The LightStream 1010 ATM switch supports configuration of dispatch sequences. You can set up dispatch characters that allow packets to be buffered, then transmitted upon receipt of a character. These characters are useful on an auxiliary port only, and then only if you have some special-purpose device hooked up.

Perform the following tasks in line configuration mode, as required for your particular system needs:

Task	Command
Define one or more characters that trigger packet transmission for the current terminal session.	dispatch-character <i>ascii-number1</i> [<i>ascii-number2</i> . . . <i>ascii-number</i>]
Set the dispatch timer for the current terminal session.	dispatch-timeout <i>milliseconds</i>

Configure Automatic Protocol Startup

To configure the LightStream 1010 ATM switch to allow an AppleTalk Remote Access (ARA), PPP, or SLIP session to start automatically, perform the following task in line configuration mode:

Task	Command
Configure a line to automatically start an ARA, PPP, or SLIP session.	autoselect { <i>arap</i> <i>ppp</i> <i>slip</i> } during login

The **autoselect** command enables the LightStream 1010 ATM switch to start an appropriate process automatically when it receives a starting character. The LightStream 1010 ATM switch detects either a Return character, which is the start character for an EXEC session, or the start character for the ARA protocol. Using the optional **during login** argument enables the user to receive the username

or password prompt without pressing the **Return** key. While the username or password is presented, you can choose to answer these prompts or to start sending packets from an autoselected protocol. Refer to the end of this chapter for configuration examples.

Note When using **autoselect**, let the activation character default to Return, and **exec-character-bits** default to 7. If you change these defaults, the application does not recognize the activation request.

Configure Terminal Banner Messages

Configure the following types of messages that will be displayed to users of terminals connected to the LightStream 1010 ATM switch by performing one or more of the following tasks:

- Configure a Message of the Day Banner
- Configure a Line Activation Message
- Configure an Incoming Message Banner
- Configure an Idle Terminal Message
- Enable or Disable the Display of Messages

The following sections explain how to configure these messages and how to suppress display of the message-of-the-day (MOTD) and line activation banners.

Configure a Message of the Day Banner

You can configure a message of the day (MOTD) to be displayed on all connected terminals. This message is displayed at login and is useful for sending messages that affect all network users, such as impending system shutdowns. To do so, perform the following task in global configuration mode:

Task	Command
Configure a message-of-the-day banner.	banner motd <i>c message c</i>

Configure a Line Activation Message

You can configure a line activation message to be displayed when an EXEC process such as line activation or an incoming connection to a virtual terminal is created. To do so, perform the following task in global configuration mode:

Task	Command
Configure a message to be displayed on terminals with an interactive EXEC.	banner exec <i>c message c</i>

Configure an Incoming Message Banner

You can configure a message to be displayed on terminals connected to reverse Telnet lines. This message is useful for providing instructions to users of these types of connections. Reverse Telnet connections are described in more detail in the section “Support Reverse TCP Connections” earlier in this chapter.

To configure the message that will be sent on incoming connections, perform the following task in global configuration mode:

Task	Command
Configure messages to display on terminals connected to reverse Telnet lines.	banner incoming <i>c message c</i>

Configure an Idle Terminal Message

You can configure messages to be displayed on a console or terminal not in use. Also called a *vacant message*, this message is different from the banner message displayed when an EXEC process is activated. To configure an idle terminal message, perform the following task in line configuration mode:

Task	Command
Display an idle terminal message.	vacant-message [<i>c message c</i>]

Enable or Disable the Display of Messages

You can control display of the MOTD and line activation banners. By default, these banners are displayed on all lines. To suppress or reinstate the display of such messages, perform one of the following tasks in line configuration mode:

Task	Command
Suppress banner display.	no exec-banner
Reinstate the display of the EXEC or MOTD banners.	exec-banner

Banner Message Examples

Suppose you want a message explaining that the server is going to be reloaded with new software. The following example shows how to use the **banner** global configuration command and **no exec-banner** line configuration command to notify your users:

```
Switch(config)#banner exec /
Enter TEXT message. End with the character '/'.
This is the Cisco System Publications and Training LS1010 Switch

Unauthorized access prohibited./
Switch(config)#banner incoming /
You are connected to a Hayes-compatible modem.

Enter the appropriate AT commands.
Remember to reset anything to change before disconnecting.
/
Switch(config)#banner motd /
The switch will go down at 6pm for a software upgrade
/
Switch(config)#line vty 0 4
Switch(config-line)#no exec-banner
Switch(config-line)#
```


Configure Telnet Capabilities

Telnet is a virtual terminal protocol that is part of the Transmission Control Protocol/Internet Protocol (TCP/IP) protocol suite that allows connections to hosts. You can configure a line to support the Telnet capabilities using one or more of the procedures described in the following sections:

- Generate a Hardware Break Signal
- Suppress Telnet Remote Echo and Go-Ahead Options
- Negotiate Speed
- Send a Telnet Synchronize Signal
- Set End-of-Line Control
- Define Telnet Connection Failure and Success Messages
- Record the Device Location
- Set Pending Output Notification
- Refuse a Connection
- Establish and Control the EXEC Process
- Display Debug Messages on the Terminal

Generate a Hardware Break Signal

A hardware Break signal is generated when a Telnet Break command is received. You can configure the LightStream 1010 ATM switch to also generate a Break on Interrupt Process command. To enable the system to generate a hardware Break signal on the RS-232 line that is associated with a reverse Telnet connection, complete the following task in line configuration mode:

Task	Command
Set the system to generate a hardware Break signal.	telnet break-on-ip

This capability is useful because several user Telnet programs can send an Interrupt Process command but cannot send a Telnet Break signal, while other programs implement a Break signal that sends an Interrupt Process command. RS-232 devices use the hardware Break signal for various purposes.

Suppress Telnet Remote Echo and Go-Ahead Options

You can cause Telnet to refuse to negotiate full-duplex, remote echo options on incoming connections. Use the following command on reverse Telnet connections to allow the LightStream 1010 ATM switch to refuse these requests from the other end. This command suppresses negotiation of the Telnet Remote Echo and Suppress Go-Ahead options. Perform the following task in line configuration mode:

Task	Command
Set a line to refuse to negotiate full-duplex, remote echo options.	telnet refuse-negotiations

Negotiate Speed

To allow the line to negotiate a bit rate on incoming connections, perform the following task in line configuration mode:

Task	Command
Set the line to negotiate speeds on incoming connections.	telnet speed <i>default-speed</i> <i>maximum-speed</i>

The LightStream 1010 ATM switch uses the *default speed* if the connected device does not specify a speed. The *maximum speed* is the highest speed the LightStream 1010 ATM switch uses.

Send a Telnet Synchronize Signal

To cause an incoming connection to send a Telnet synchronize signal when it receives a Telnet Break signal, complete the following task in line configuration mode:

Task	Command
Cause an incoming connection to send a Telnet synchronize signal when it receives a Telnet Break signal.	telnet sync-on-break

This capability is used very rarely to ensure the ordering of Break reception with respect to data characters sent after the Break signal.

Set End-of-Line Control

To configure the LightStream 1010 ATM switch to send a carriage return (CR) as a CR followed by a NULL instead of a CR followed by a line feed (LF), complete the following task in line configuration mode:

Task	Command
Send a CR followed by a NULL instead of a LF.	telnet transparent

This capability is useful for coping with different interpretations of end-of-line handling in the Telnet protocol specification.

Define Telnet Connection Failure and Success Messages

You can define a message that is displayed when a Telnet connection to a specified host fails or succeeds. To do so, perform one or both of the following tasks in global configuration mode:

Task	Command
Define a message that the LightStream 1010 ATM switch displays whenever an attempt to connect to the specified host fails.	busy-message <i>hostname d message d</i>
Define a message that the LightStream 1010 ATM switch displays whenever an attempt to connect to the specified host succeeds.	login-string <i>hostname c message</i> [%secp] [%secw] [%b] c

With the **login-string** options, you can set a pause, prevent a user from issuing commands during a pause, send a Break character, and use a percent sign (%) in the login string.

Record the Device Location

You can record the location of a serial device by performing the following task in line configuration mode. The text provided for the location appears in the output of the EXEC monitoring commands.

Task	Command
Record the location of a serial device.	location <i>text</i>

Set Pending Output Notification

You can set up a line to inform a user who has multiple, concurrent Telnet connections when output is pending on a connection other than the current one. To do so, perform the following task in line configuration mode:

Task	Command
Set up a line to notify a user of pending output.	notify

Refuse a Connection

You can create a message that says the line is in use by performing the following task in line configuration mode:

Task	Command
Define a line-in-use message.	refuse-message <i>c message c</i>

Establish and Control the EXEC Process

By default, the LightStream 1010 ATM switch starts an EXEC process on all lines; however, commands are available to control EXEC processes, as follows:

- Turn the EXEC on or off.

When you want to allow an outgoing connection *only* for a line, use the **no exec** command. When you try to use a line with the EXEC off, you will get no response when pressing the **Return** key at the login screen.

- Set the idle terminal timeout interval.

The EXEC command interpreter waits for a specified interval of time until you begin input. If no input is detected, the EXEC resumes the current connection. If no connections exist, the EXEC returns the terminal to the idle state and disconnects the incoming session.

To control the EXEC as stated above, perform the following tasks in line configuration mode:

Task	Command
Turn the EXEC on or off.	exec or no exec
Set the idle terminal timeout interval.	exec-timeout <i>minutes</i>

Example

The following example configures virtual terminal line number 0 with an executive timeout of 5 minutes:

```
Switch(config)#line vty 0
Switch(config-line)#exec-timeout 5
```

Display Debug Messages on the Terminal

The EXEC provides the ability to display **debug** command output and system error messages on the current terminal. To enable this feature, perform the following task in EXEC mode:

Task	Command
Display debug command output and system error messages on the current terminal.	terminal monitor ¹

1. This command is documented in the *LightStream 1010 ATM Switch Command Reference*.

Refer to the *LightStream 1010 ATM Switch Debug Command Reference* publication for details on **debug** commands and output.